




**Quartz Lamps**



**Caster Wheels**



**Height Adjustable**

### **ANCHO 1820 / 2230/ 2840**

Ancho is M&R Global's versatile freestanding quartz flash cure system. It has a universal design that can fit most brands' presses. An adjustable sensor switch can be positioned on either side of the flash cure unit, activating the flash when the printing pallet approaches. It uses medium wave filament quartz lamps and flash cure duration can be controlled by an analog timer.

All the lamps can be individually controlled with the toggle switches present on the flash body. Lamp height can be adjusted up to 121 cm (48"). Smooth rolling, locking casters makes moving the flash fast & easy.

## SPECIFICATIONS

	<b>ANCHO 1820</b>	<b>ANCHO 2230</b>	<b>ANCHO 2432</b>	<b>ANCHO 2840</b>	<b>ANCHO 3230</b>	<b>ANCHO 3248</b>
<b>Curing Area</b>	46 x 51 cm (18" x 20")	56 x 76 cm (22" x 30")	61 x 81 cm (24" x 32")	71 x 101 cm (28" x 40")	80 x 76 cm (32" x 30")	80 x 120 cm (32" x 48")
<b>Electrical Requirements<sup>1</sup></b>	208-230 V, 3 ph, 38 A, 50/60 Hz, 12.0 Kw 380-415 V, 3 ph, 22 A, 50 Hz, 12.0 kW	208-230 V, 3 ph, 49 A, 50/60 Hz, 15.6 Kw 380-415 V, 3 ph, 28.5 A, 50 Hz, 15.6 kW	208-230 V, 3 ph, 57 A, 50/60 Hz, 18 Kw 380-415 V, 3 ph, 33 A, 50 Hz, 18 kW	380-415 V, 3 ph, 40 A, 50 Hz, 21.6 kW	380-415 V, 3 ph, 33 A, 50 Hz, 18 kW	380-415 V, 3 ph, 49 A, 50 Hz, 27 kW
<b>Machine Dimension (L x W)</b>	102 x 61 cm (43" x 24")	124 x 68 cm (48.9" x 26.8")	129 x 71 cm (50.8" x 28")	155 x 81 cm (61" x 32")	130 x 92 cm (51.2" x 36.2")	175 x 92 cm (68.9" x 36.2")
<b>Machine Height</b>	101 cm - 121 cm (Adjustable)	101 cm - 121 cm (Adjustable)	101 cm - 121 cm (Adjustable)	101 cm - 121 cm (Adjustable)	101 cm - 121 cm (Adjustable)	101 cm - 121 cm (Adjustable)
<b>Weight</b>	58 kg (128 lbs)	70 kg (154 lbs)	78 kg (172 lbs)	102 kg (225 lbs)	98 kg (216 lbs)	115 kg (254 lbs)

<sup>1</sup> Use uninterruptible power supply (UPS) to safeguard machine from voltage fluctuation out of main supply.  
If incoming voltage differs from the voltage(s) listed in the brochure, calculate amperage accordingly

**M&R Printing Equipment, Inc. • [www.mrprint.com](http://www.mrprint.com)**

440 Medinah Road, Roselle, Illinois 60172-2329 USA

**DCC Group • [www.mrprintglobal.com](http://www.mrprintglobal.com)**

802, Kamla Executive Park, JB Nagar, Andheri (E), Mumbai, 400059, India

**USA: 800-736-6431 / 630-858-6101 • Outside USA: +1-847-967-4461 • India: +91 98719-88775**

M&R Printing Equipment, Inc. and its subsidiaries (hereinafter M&R), believe the information in this advertisement to be accurate at publication, though it does not purport to list all manufacturing and specification variations, nor does it assume liability resulting from incompleteness or inaccuracy. M&R reserves the right to change specifications without notice. M&R expressly disclaims any liability for damages, consequential or incidental, from purchase, installation, servicing, and/or use of any product/service based upon information herein. No warranties of merchantability or fitness for a particular purpose are made or are to be implied from the information herein. No information herein may be reproduced or used in any manner without the prior, express written consent of M&R in each case. Copyright 2023 M&R Printing Equipment, Inc. All rights reserved. 20250515